

SID

Factory: Rot am See

Article:

ML14

Provided:

Customer:

Date:

24.04.2026



WÜRTH  
ELEKTRONIK  
MORE THAN  
YOU EXPECT

Processtechnology: B: undefined

Material Text	Mat. Nr.	µm	Stackup	Process overview
---------------	----------	----	---------	------------------

A-RS Kupferfolie-018my 330x490mm	50200238	18	VS	1	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	238		2	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		3	
		18	L2		
C-RS-FR4-ML-0.203mm-018+018-TG150-HF-...	50203027	203		4	A01
		18	L3		
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	231		5	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		6	
		18	L4		
C-RS-FR4-ML-0.203mm-018+018-TG150-HF-...	50203027	203		7	A02
		18	L5		
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	231		8	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		9	
		18	L6		
C-RS-FR4-ML-0.203mm-018+018-TG150-HF-...	50203027	203		10	A03
		18	L7		
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	231		11	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		12	B00
		18	L8		
C-RS-FR4-ML-0.203mm-018+018-TG150-HF-...	50203027	203		13	A04
		18	L9		
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	231		14	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		15	
		18	L10		
C-RS-FR4-ML-0.203mm-018+018-TG150-HF-...	50203027	203		16	A05
		18	L11		
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	231		17	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		18	
		18	L12		
C-RS-FR4-ML-0.203mm-018+018-TG150-HF-...	50203027	203		19	A06
		18	L13		
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	238		20	
C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B...	50203001	0		21	
A-RS Kupferfolie-018my 330x490mm	50200238	18	RS	22	

Thickness after Pressing

B00:

3090 µm

Tol+:

320 µm

Tol-:

320 µm

Dmax:

3410 µm

Dmin:

2770 µm

Thickness over all

0 µm

Tol+:

0 µm

Tol-:

0 µm

Dmax:

0 µm

Dmin:

0 µm

Demand for customer

Thickness (D):

3200 µm

Tol+:

320 µm

Tol-:

320 µm

Dmax:

3520 µm

Dmin:

2880 µm

Measuring point: (05) over SM and galv. Cu; both sides

nominal:

3101 µm

Version 1.2.20.35

© Würth Elektronik