

SID

Factory: Rot am See

Article:

ML6

Provided:

Customer:

Date:

03.04.2026

WÜRTH
ELEKTRONIK
MORE THAN
YOU EXPECT

Processtechnology: B: undefined

| Material Text | Mat. Nr. | µm | Stackup | Process overview |
|---------------|----------|----|---------|------------------|
|---------------|----------|----|---------|------------------|

| | | | | | |
|--|----------|-----|----|----|-----|
| A-RS Kupferfolie-070my 330x490mm | 50200246 | 70 | VS | 1 | |
| C-RAS-FR4-PP-1080-H63-TG150-HF-EM-37B... | 50203000 | 229 | | 2 | |
| C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B... | 50203001 | 0 | | 3 | |
| C-RAS-FR4-PP-1080-H63-TG150-HF-EM-37B... | 50203000 | 0 | | 4 | |
| | | 105 | L2 | | |
| B-SHJ-FR4-ML-0.10mm-105+105-TG150-HF-... | 50203118 | 100 | | 5 | A01 |
| | | 105 | L3 | | |
| C-RAS-FR4-PP-1080-H63-TG150-HF-EM-37B... | 50203000 | 257 | | 6 | |
| A-RAS-FR4-PP-7628-H45-TG150-HF-EM-37B... | 50203002 | 0 | | 7 | |
| C-RAS-FR4-PP-1080-H63-TG150-HF-EM-37B... | 50203000 | 0 | | 8 | |
| | | 105 | L4 | | |
| B-SHJ-FR4-ML-0.10mm-105+105-TG150-HF-... | 50203118 | 100 | | 9 | A02 |
| | | 105 | L5 | | |
| C-RAS-FR4-PP-1080-H63-TG150-HF-EM-37B... | 50203000 | 229 | | 10 | |
| C-RAS-FR4-PP-2116-H53-TG150-HF-EM-37B... | 50203001 | 0 | | 11 | |
| C-RAS-FR4-PP-1080-H63-TG150-HF-EM-37B... | 50203000 | 0 | | 12 | |
| A-RS Kupferfolie-070my 330x490mm | 50200246 | 70 | RS | 13 | |

B00:

Thickness after Pressing

B00:

1440 µm

Tol+:

155 µm

Tol-:

155 µm

Dmax:

1595 µm

Dmin:

1285 µm

Thickness over all

0 µm

Tol+:

0 µm

Tol-:

0 µm

Dmax:

0 µm

Dmin:

0 µm

Demand for customer

Thickness (D):

1550 µm

Tol+:

155 µm

Tol-:

155 µm

Dmax:

1705 µm

Dmin:

1395 µm

Measuring point: (05) over SM and galv. Cu; both sides

nominal:

1475 µm

Version 1.2.20.35

© Würth Elektronik