

# SID

Factory: Rot am See

Article:

ML2

Provided:

Customer:

Date:

28.04.2026

**WÜRTH  
ELEKTRONIK**  
MORE THAN  
YOU EXPECT

Material Text	Mat. Nr.	µm	Stackup	Process overview
---------------	----------	----	---------	------------------

C-RS Pyralux AP8525E 305x457mm 0.050mm... 50200050

18
50
18

VS

1

RS



A00

Thickness after Pressing

A00:

110 µm

Tol+:

50 µm

Tol-:

50 µm

Dmax:

160 µm

Dmin:

60 µm

Thickness over all

0 µm

Tol+:

0 µm

Tol-:

0 µm

Dmax:

0 µm

Dmin:

0 µm

Demand for customer

Thickness (D):

170 µm

Tol+:

50 µm

Tol-:

50 µm

Dmax:

220 µm

Dmin:

120 µm

Measuring point:

(05) over SM and galv. Cu; both sides

nominal:

86 µm

Version 1.2.20.35

© Würth Elektronik

**Please pay attention if you order a PCB without PTH: the thickness will be approx. 0.115mm**